I hree year limited warranty. Rubber non-skid bottom. Rugged die cast metal case. Adapter jack for A.C. operation. No tools, easy access battery compartment. pattery condition. LED battery indicator shows the status of the effect and FET switching for clickless insertion into the signal path.

SARUTAAA

battery, attach the DOD PS125 to the AC adapter jack. another effects device. To eliminate the need for a 9-volt the output of the FX40B to your amp or to the input of Connect your guitar to the input of the FX40B. Connect

CONNECTING THE FX40B

level slider lets you adjust the equalization you apply. This effect pedal is a graphic equalizer. Each slider cuts

SEOD 804 XF EHT TAHW



PS125 power supply to eliminate the need for batteries.) JACKS: INPUT, OUTPUT, A.C. ADAPTER. (Use the DOD .peidsne LED INDICATOR: Lights up when the equalization unit is

lets you compensate for inadequacies in your P.A. The sound or tone of your P.A. system before feedback, and more gain from your P.A. system before feedback, and beggi. The graphic equalizer allows you to change the graphically shows the equalization curve created by the change the sound, the pattern made by the slider knobs one level control slider. When the sliders are moved to spectrum. The FX40B has seven equalizing sliders and tone control which only attects a narrow part of the sound or boosts a one octave wide band. Each band is like a

1600, and 3200 Hz. FX40B FREQUENCY CENTERS: 100, 200, 400, 800, octave wide) by up to 18 dB. cuts or boosts its respective band of frequencies (one tone of the sound at specific frequencies. Each control equalization on one octave centers allow you to adjust the EQUALIZATION CONTROLS: The seven bands of

equalizer to compensate for level increases or decreases due to the equalisation applied to the signal. LEVEL CONTROL: Adjusts the output of the graphic

> DECLARATION OF CONFORMITY Manufacturer's Name: DOD Electronics Corporation Manufacturer's Address: 8760 S. Sandy Parkway Sandy, Utah 84070, USA

> > declares that the produc

Product Options: All (requires a Class II power adapter that conforms to the requirements of EN 60065 EN 60742, or equivalent).

Safety: EN 60065 (1993) IEC65 (1985) with Amendments 1,2,3

EMC: EN 55013: (1990) EN 55020: (1991)

Supplementary Information:

The product herewith complies with the requirements of the Low Voltage Directive 73/23/EEC and the EMC Directive 89/336/EEC as amended by directive 93/68/EEC.

DOD Electronics Corporation President of DOD 8760 S. Sandy Parkway Sandy, Utah 84070, USA

Effective: August 26, 1997

European Contact: Your Local DOD Sales and Service Office or

International Sales Office 3 Overlook Drive #4 Amherst, New Hampshire 03031, USA Tel (603) 672-4244

Fax (603) 672-4246

DOD Electronics Corporation

8760 South Sandy Parkway

Sandy, Utah 84070 Telephone (801) 566-8800 FAX (801) 566-7005 International Distribution 3 Overlook Drive Unit 4 Amherst, New Hampshire 03031

USA

FAX (603) 672-4246 Copyright © 1998 DOD Electronics Corporation Printed 2/98 FX40B 18-0016-C

Product Name: FX40B

FOOT SWITCH: Switches the equalization IN/OUT of the

CONTROLS

ulad lengis

overall sound is changed the least amount. done by cutting only one band of frequencies so that the Cutting down the feedback in your P.A. on one channel is .A.9 nuoy

system, or cut down feedback from one input channel in chain, or make up for something lacking in the sound chain, it can be used to change the overall sound of the

When the graphic equalizer is used at the end of an effects next effect.)

(Be sure to reduce the level to avoid clipping going into the the sound from a particular effect unit.

A state of the state of the

boosting the level from an acoustical pickup.

to brighten its sound by boosting its upper frequencies and Used with an acoustical guitar the equalizer can be used านอนเกมร์น

chain, it usually is used to change the basic sound of your When the equalizer is used at the beginning of an effect middle and at the end of the effect chains.


The graphic equalizer may be used at the beginning, in the Juew no/

Experiment with your equalizer to create new sounds that expected? Agreat deal of trial-and-error is involved in learning what this signal processor can do for you. it makes in the sound. Does the setting do what you move one slider at a time and listen carefully to the change I he main idea in learning how to use the equalizer is to


OPERATION OF THE FX40B

SETTING FOR A BIG THICK SOUND FROM A

DISTORTION EFFECT



BRIGHTENING AN ELECTRIC/ACOUSTIC



DOD Warranty

• The FX40B battery is in use whenever the INPUT jack is plugged in. If you are not using the FX40B, be sure to unplug the cable from the INPUT jack. This will prevent unnecessary battery drain.

· Remove the battery whenever the unit is not going to be used for an extended period of time. This will prevent possible damage due to leaking battery fluids.

IMPORTANT NOTES

. If the FX40B fails to switch in or out or the LED indicator stays lit, the battery needs to be replaced.

. Use of any AC adapter other than the DOD PS125 will void the warranty of this product.

 Unauthorized repair of the FX40B will void the warranty. Should your FX40B require service, contact your DOD FX pedal dealer for return / repair information.

 The warranty registration card must be mailed within ten days after purchase date to validate this warranty.

2. DOD warrants this product, when used solely within the U.S., to be free from defects in materials and workmanship under normal use and service

3. DOD liability under this warranty is limited to repairing or replacing defective materials that show evidence of defect, provided the product is returned through the original dealer, where all parts and labor will be covered up to a period of three years. The company shall not be liable for any consequential damage as a result of the product's use in any circuit or assembly.

4. Proof-of-purchase is considered to be the burden of the

5. DOD reserves the right to make changes in design or make additions to or improvements upon this product

without incurring any obligation to install the same on

products previously manufactured.

consumer.